

# Controllers for Motorised Video Screens

## SCR-04

- Both 2-pushbutton and V+ trigger control of up/down displacement
- Mains power-on determination of up or down screen command



## SCR-04 PACK



TXIR-02

+



IRR-05

+



SCR-04



## SCR-11

+

- Controller for motorized video screens which provides both I/R remote control (internal receiver or optional external receiver) and/or momentary contact control (push-buttons, relay contacts, open collectors, etc.)
- 3 pulsed commands : up, down and stop



# Technical Specifications

## Comparative Table

	<b>SCR-04</b>	<b>SCR-11</b>
I/R Remote Controlled	Yes*	Yes**
STOP Command	No	Yes
V+ Trigger Command	Yes	No
0V Command	Yes	Yes
Mains Power-on Command (screen up or down)	Yes	Yes
Momentary contact Command (push buttons or dry contacts)	Yes	Yes
<i>Case size (MM/Inches) :</i>		
L	120/4.7	150/5.3
W	50/1.8	100/3.5
H	27/1.1	31/1.2
Mass (Grs)	140	411

## Common Specifications

- Direct connection to 230V mains supply
- Motor switching current : 5.0 Amp max.
- Internal relay contact protection
- Quality detachable connectors for mains input and screen output
- Storage Temperature : -20° to +60° C (-4° to +140° F)
- Operating Temperature : 0° to 40°C (32° to 104° F)

\* *With the IRR-05 receiver and I/R remote control TXIR-02*

\*\* *With the I/R remote control TXIR-03*

We reserve the right to modify technical specifications without prior notice

## Product References

SCR-04	Universal motorized projection screens controller with momentary contact and trigger control
SCR-11	Motorized projection screens controller, internal I/R receiver, I/R remote control option (TXIR-03)
SCR-04 Pack	SCR-04 Controller, IRR-05 I/R Receiver & TXIR-02 I/R Remote Control